ARCHITECTURAL STRUCTURES I:

STATICS AND STRENGTH OF MATERIALS

ENDS 231

DR. ANNE NICHOLS

FALL 2007

.lecture



rigid body equilibrium

Rigid Bodies and Supports

Architectural Structures I ENDS 231

F2005abn


Equilibrium rigid body

- doesn't deform
- coplanar force systems
- static:

$$R_{x} = \sum F_{x} = 0$$

$$R_{y} = \sum F_{y} = 0$$

$$M = \sum M = 0$$



Rigid Bodies and Supports 4

Architectural Structures I

S2004abn

Free Body Diagram


- FBD (sketch)
- tool to see all forces on a body or a point including
 - external forces
 - weights

Rigid Bodies and Supports 10

- force reactions
- external moments
- moment reactions
- internal forces

Free Body Diagram

- determine body
- FREE it from:
 - ground
 - supports & connections
- draw all external forces acting ON the body
 - reactions
 - applied forces
 - gravity



Rigid Bodies and Supports 11

Architectural Structures I

S2004abn

(Example 1)


Free Body Diagram

- include relevant geometry
 - guidelines helpful to see moment arms
- name and/or color the unknown
 - forces
 - moments
 - angles
- solve up to 3 equations

Rigid Bodies and Supports 7

Architectural Structures I ENDS 231 S2004abn

Supports and Connections




Reactions

- result of applying force
- unknown size
- connection or support type
 - known direction
 - related to motion prevented




Supports and Connections



FBD Example

- 500 lb known
- $pin A_x$, A_y
- smooth surface -B at 4:3
- 3 equations
- sum moments at
 - -A?
 - -B?
- (B_x)




Rigid Bodies and Supports 16

Architectural Structures I FNDS 231

S2004abn

Recognizing Reactions



Rigid Bodies and Supports 17

Architectural Structures I ENDS 231

S2004abn

Moment Equations

- sum moments at intersection where the most forces intersect
- multiple moment equations may not be useful
- combos:

$$\sum F_{x} = 0 \qquad \sum F = 0 \qquad \sum M_{1} = 0$$

$$\sum F_{y} = 0 \qquad \sum M_{1} = 0 \qquad \sum M_{2} = 0$$

$$\sum M_{1} = 0 \qquad \sum M_{2} = 0 \qquad \sum M_{3} = 0$$


Rigid Bodies and Supports 17

Rigid Bodies and Supports 18

Architectural Structures I ENDS 231

S2004abn

Recognizing Reactions



ENDS 231


Architectural Structures I


S2004abr

Constraints

- completely constrained
 - doesn't move
 - may not be statically determinate
- improperly or partially constrained
 - has ≤ unknowns
 - can't solve









Rigid Bodies and Supports 14


Architectural Structures I ENDS 231

S2004abn

Partial Constraints











Constraints

- overconstrained
 - won't move
 - can't be solved with statics
 - statically indeterminate to nth degree






Rigid Bodies and Supports 15

Architectural Structures I ENDS 231 S2004abn

Two Force Rigid Bodies

- equilibrium:
 - forces in line, equal and opposite




Rigid Bodies and Supports 22

Architectural Structures I ENDS 231 S2004abn

S2004abn

Three Force Rigid Bodies

- equilibrium:
 - concurrent or parallel forces




Rigid Bodies and Supports 18

Architectural Structures I ENDS 231 S2004abn

Cable Reactions

- equilibrium:
 - more reactions (4) than equations
 - but, we have slope relationships
 - x component the same everywhere



Rigid Bodies and Supports 24

Architectural Structures I ENDS 231 S2004abn